

# ENERGY 1500 START



- Battery charger and starter for 12/24V WET batteries and rapid cranking of all types of cars, vans, light goods vehicles, excavators, tractors and lorries.-
- Fast (BOOST) charge and rapid cranking.
- Remote control. Timer to program timed BOOST charge and avoid overloading the battery.
- Display of charging and cranking current.
- Protection against overcharging and pole inversion.

## DESCRIPTION

Battery charger and starter for charging free electrolyte batteries (WET) with 12V/24V voltage and starting all kinds of cars, vans, light trucks, earth moving equipment, tractors and trucks.

Features:

- choice of normal charge, quick charge (BOOST), quick start
- timer for quick charge
- remote control
- display of charging and starting current
- protection against overloads and polarity reversal.



## TECHNICAL DATA

<b>CODE</b>	CODE 829009	<b>V<sub>3PH</sub></b>	THREEPHASE MAINS VOLTAGE 230 / 400 V	<b>F</b>	MAINS FREQUENCY 50 / 60 Hz
<b>P<sub>CHARGE</sub></b>	CHARGING ABSORBED POWER 7 kW	<b>P<sub>START</sub></b>	STARTING ABSORBED POWER 44 kW		CHARGE AND STARTING VOLTAG. 12 / 24 V
<b>A<sub>EFF</sub></b>	EFFECTIVE CHARGING CURRENT 150 / 250 A	<b>A<sub>EN</sub></b>	RATED CHAR.CUR.EN60335-2-29 130 / 220 A	<b>A<sub>1V/C</sub></b>	START CUR.1V/C EN60335-2-29 1000 / 1300 A
<b>A<sub>START MAX</sub></b>	MAX STARTING CURRENT 1700 / 2000 A		MIN.RATED REFERENCE CAPAC. 70 Ah		MAX.RATED REFERENCE CAPAC. 2200 / 4000 Ah
	ADJUSTMENT POSITIONS 6		DIMENSIONS (LxWxH) 38 x 56 x 88,5 cm		WEIGHT 69 kg

## ON REQUEST ACCESSORIES



FUSES 300A 10 PCS  
802129

DOWNLOAD



CATALOG IMAGE



INSTRUCTION MANUAL



SPARE PARTS LIST