

ALPINE 20 BOOST



12V

24V

- Battery charger for WET 12/24V batteries. With ammeter and normal or fast (BOOST) charge selector. 300W.
- Protection against overcharging and pole inversion.

DESCRIPTION

Battery charger for charging free electrolyte batteries (WET) with 12V/24V voltage.

Protected against overloads and polarity reversal.

Equipped with selector for normal or quick (BOOST) charge. Equipped with ammeter.



TECHNICAL DATA

CODE	CODE 807546	V_{1PH}	SINGLEPHASE MAINS VOLTAGE 230 V	F	MAINS FREQUENCY 50 / 60 Hz
P	CHARGING ABSORBED POWER 300 W		CHARGING VOLTAGE 12 / 24 V	A_{EFF}	EFFECTIVE CHARGING CURRENT 18 / 12 A
A_{EN}	RATED CHAR.CUR.EN60335-2-29 12 / 8 A		MIN.RATED REFERENCE CAPAC. 30 / 20 Ah		MAX.RATED REFERENCE CAPAC. 225 / 180 Ah
	ADJUSTMENT POSITIONS 2		DIMENSIONS (LxWxH) 22,5 x 29 x 20,5 cm		WEIGHT 6,9 kg

SUPPLIED ACCESSORIES



COLORADO 40R POSITIVE CLAMP 40A
712623



COLORADO 40B WORK CLAMP 40A
712624

ON REQUEST ACCESSORIES



FUSES 20A 10 PCS
802257

DOWNLOAD



CATALOG IMAGE



INSTRUCTION MANUAL



SPARE PARTS LIST