

## ALPINE 30 BOOST



12V

24V

- Battery charger for WET 12/24V batteries. With ammeter and normal or fast (BOOST) charge selector. 800W.
- Protection against overcharging and pole inversion.

## DESCRIPTION

Battery charger for charging free electrolyte batteries (WET) with 12V/24V voltage.

Protected against overloads and polarity reversal.

Equipped with selector for normal or quick (BOOST) charge. Equipped with ammeter.



## TECHNICAL DATA

<b>CODE</b>	CODE 807547	<b>V<sub>1PH</sub></b>	SINGLEPHASE MAINS VOLTAGE 230 V	<b>F</b>	MAINS FREQUENCY 50 / 60 Hz
<b>P</b>	CHARGING ABSORBED POWER 800 W		CHARGING VOLTAGE 12 / 24 V	<b>A<sub>EFF</sub></b>	EFFECTIVE CHARGING CURRENT 30 A
<b>A<sub>EN</sub></b>	RATED CHAR.CUR.EN60335-2-29 20 A		MIN.RATED REFERENCE CAPAC. 15 Ah		MAX.RATED REFERENCE CAPAC. 400 Ah
	ADJUSTMENT POSITIONS 3		DIMENSIONS (LxWxH) 22,5 x 29 x 20,5 cm		WEIGHT 8,6 kg

## ON REQUEST ACCESSORIES



FUSES 15A 10 PCS  
802256

DOWNLOAD



CATALOG IMAGE



INSTRUCTION MANUAL



SPARE PARTS LIST