

## DYNAMIC 420 START



- Battery charger and starter for 12/24V WET batteries and rapid cranking of all types of cars, vans, light goods vehicles. 400A max.-
- Normal charge, fast (BOOST) charge, rapid cranking selection.
- Display of charging and cranking current.
- Protection against overcharging and pole inversion.

## DESCRIPTION







Battery charger and starter for charging free electrolyte batteries (WET) with 12V/24V voltage and starting all kinds of cars, vans and light trucks.

Features:

- choice of normal charge, quick charge (BOOST), quick start
- display of charging and starting current
- protection against overloads and polarity reversal.



## TECHNICAL DATA

<b>CODE</b>	CODE 829382	<b>V<sub>1PH</sub></b>	SINGLEPHASE MAINS VOLTAGE 230 V	<b>F</b>	MAINS FREQUENCY 50 / 60 Hz
<b>P<sub>CHARGE</sub></b>	CHARGING ABSORBED POWER 2 kW	<b>P<sub>START</sub></b>	STARTING ABSORBED POWER 12 kW		CHARGE AND STARTING VOLTAG. 12 / 24 V
<b>A<sub>EFF</sub></b>	EFFECTIVE CHARGING CURRENT 90 A	<b>A<sub>EN</sub></b>	RATED CHAR.CUR.EN60335-2-29 60 A	<b>A<sub>1V/C</sub></b>	START CUR.1V/C EN60335-2-29 300 A
<b>A<sub>START MAX</sub></b>	MAX STARTING CURRENT 400 A		MIN.RATED REFERENCE CAPAC. 20 Ah		MAX.RATED REFERENCE CAPAC. 1000 Ah
	ADJUSTMENT POSITIONS 4		DIMENSIONS (LxWxH) 30,5 x 36 x 63 cm		WEIGHT 16,4 kg

## SUPPLIED ACCESSORIES



COLORADO 150B WORK CLAMP 150A  
712001



COLORADO 150R POSITIVE CLAMP 150A  
712002

ON REQUEST ACCESSORIES



FUSES 80A 20 PCS  
802260

DOWNLOAD



CATALOG IMAGE



INSTRUCTION MANUAL



SPARE PARTS LIST