

ENERGY 650 START



- Battery charger and starter for 12/24V WET batteries and rapid cranking of all types of cars, vans, light goods vehicles, excavators, tractors and lorries.-
- Fast (BOOST) charge and rapid cranking.
- Remote control. Timer to program timed BOOST charge and avoid overloading the battery.
- Display of charging and cranking current.
- Protection against overcharging and pole inversion.

DESCRIPTION

Battery charger and starter for charging free electrolyte batteries (WET) with 12V/24V voltage and starting all kinds of cars, vans, light trucks, earth moving equipment, tractors and trucks.

Features:

- choice of normal charge, quick charge (BOOST), quick start
- timer for quick charge
- remote control
- display of charging and starting current
- protection against overloads and polarity reversal.



TECHNICAL DATA

CODE	CODE 829385	V_{3PH}	THREEPHASE MAINS VOLTAGE 230 / 400 V	F	MAINS FREQUENCY 50 / 60 Hz
P_{CHARGE}	CHARGING ABSORBED POWER 2,5 kW	P_{START}	STARTING ABSORBED POWER 20 kW		CHARGE AND STARTING VOLTAG. 12 / 24 V
A_{EFF}	EFFECTIVE CHARGING CURRENT 100 A	A_{EN}	RATED CHAR.CUR.EN60335-2-29 80 A	A_{1V/C}	START CUR.1V/C EN60335-2-29 640 A
A_{START MAX}	MAX STARTING CURRENT 1000 A		MIN.RATED REFERENCE CAPAC. 20 Ah		MAX.RATED REFERENCE CAPAC. 1600 / 800 Ah
	ADJUSTMENT POSITIONS 5		DIMENSIONS (LxWxH) 36,5 x 46 x 75,5 cm		WEIGHT 38 kg

ON REQUEST ACCESSORIES



FUSES 100A 10 PCS
802131

DOWNLOAD



CATALOG IMAGE



INSTRUCTION MANUAL



SPARE PARTS LIST