

SPRINTER 3000 START



ELEMENTS



- Battery charger and starter: WET, START-STOP 12/24V battery charger and rapid ignition of all types of vehicles, vans, etc. (300A max).-----
- Normal charge, boost, rapid ignition selection.--
- Display of charging and ignition current.
- Protection against overcharging and pole inversion.

DESCRIPTION

Battery charger and starter for charging free electrolyte batteries (WET) with 12V/24V voltage and starting all kinds of cars, vans and light trucks.

Features:

- Choice of normal charge, quick charge (BOOST), quick start;
- Display of charging and starting current;
- Protection against overloads and polarity reversal.



TECHNICAL DATA

CODE	CODE 829390	V_{1PH}	SINGLEPHASE MAINS VOLTAGE 230 V	F	MAINS FREQUENCY 50 / 60 Hz
P_{CHARGE}	CHARGING ABSORBED POWER 1 kW	P_{START}	STARTING ABSORBED POWER 6,4 kW		CHARGE AND STARTING VOLTAG. 12 / 24 V
A_{EFF}	EFFECTIVE CHARGING CURRENT 45 A	A_{EN}	RATED CHAR.CUR.EN60335-2-29 31 A	A_{1V/C}	START CUR.1V/C EN60335-2-29 180 A
A_{START MAX}	MAX STARTING CURRENT 300 A		MIN.RATED REFERENCE CAPAC. 20 Ah		MAX.RATED REFERENCE CAPAC. 700 Ah
	ADJUSTMENT POSITIONS 3		DIMENSIONS (LxWxH) 32 x 38 x 78 cm		WEIGHT 16,45 kg

SUPPLIED ACCESSORIES



COLORADO 150B WORK CLAMP 150A
712001



COLORADO 150R POSITIVE CLAMP 150A
712002

ON REQUEST ACCESSORIES



FUSES 50A 20 PCS
802259

DOWNLOAD



CATALOG IMAGE



INSTRUCTION MANUAL



SPARE PARTS LIST

USEFUL LINKS



VIDEO